

Siemens Hicom and Hipath Pabx.

Operator / Administrators Programming Guide.

At the Operators Phone,
Do not pickup the Handset,
Press ***95** on the keypad,
The display reads
"System Administration"
"User"

Enter 1, Tick, Tick.

Note: For Older model systems the screen will show User Data?

Simply press Tick.

The display shows a menu,

Note: (n) = a number (1 – 20)

(n) = System Speed Dials – or - "Central Abb Dial?" depending on your Pabx model.

(n) = Time

(n) = Date

(n) = CDR

(n) = Extension Names

(n) = Text Messages

Press (n) on the keypad or scroll the cursor using the < > **keys** to highlight your choice then press the Tick Key.

Follow the screen prompts!

To Programme Time

Select (n) = Time

The display will show:

Format: hhmm: xxxx with xxxx being the current time entry

Display will show * = **Change?**

Press Tick to change the entry

The display will show:

Format: hhmm:

Enter the correct Time using 24 hr clock e.g 2.00pm = 1400

The display will show:

Save Entry? - or - Confirm Entry? depending on your Pabx model

Press Tick to save /confirm the entry.

You can now proceed to alter any of the other programming options:

Date, Speed Dials, Extension Names or Text Messages

By simply following the screen prompts and responding to them appropriately.